

## Model DR

Part Number (P/N):  
**DR118 + Connector**

### Two-Way Radio Antenna

#### Features:

- 1/4 wave PVC
- High durability and high efficiency
- Flexible

#### Specifications:

All Centurion products are designed for maximum efficiency and are Customizable and scalable to meet your requirements.

|                          |                        |
|--------------------------|------------------------|
| <b>Frequency</b>         | <b>VHF</b>             |
| <b>Polarization</b>      | Vertical               |
| <b>Nominal Impedance</b> | 50 ohms                |
| <b>VSWR</b>              | 1.5:1 max at resonance |
| <b>RF Power Handling</b> | 50 watts               |
| <b>Temperature Range</b> | -40°C to +85°C         |
| <b>Length</b>            | 19"                    |
| <b>Drop Test</b>         | 1M                     |

The DR model antenna is available in the following frequency with the listed connectors.

Order by antenna model, frequency and connector.

For example: DR118BN.

| Part Number | Frequency Band | Connectors  |
|-------------|----------------|-------------|
| DR118       | 118-225 MHz    | BN, MX & SF |



Model DR



Specifications subject to change without notice.

Model DR - 9/5/03